



## CUSTOMER SUPPORT BULLETIN

---

### Telos Part # 9156 - Zephyr Terminal Adapter Card with Built-in NT-1 Upgrade Instructions

21 February 2000

*Note: Zephyr firmware version 2.56 or later is required to use this Terminal Adaptor version.*

Installation procedure:

1. Power Zephyr off and remove the AC Mains power connector.
2. Remove top cover.
3. Locate the ISDN Terminal Adapter card that is currently installed in the position closest to the side panel and remove the capture screws attaching the card to the back panel of the Zephyr. Carefully remove the card from its connectors on the motherboard by pulling straight up. If there is no card located in this position remove the two screws from the blank cover plate and remove it.
4. Install the new ISDN Terminal Adapter Card with Built-in NT-1 in this slot. Install the capture screws.
5. Replace top cover and connect AC Mains power connector.
6. Power the Zephyr on.

Thank you for your support of Telos Systems. For more information see our web site [www.zephyr.com](http://www.zephyr.com) or email [support@telos-systems.com](mailto:support@telos-systems.com), or [europe@telos-systems.com](mailto:europe@telos-systems.com).